


Symbol	Function	SYS CODE: 01 Code (RC5)
	Stand By	0C
	HDMI 1	37
	HDMI 2	36
	HDMI 3	32
	HDMI 4	34
	Direct Programme	01
	Direct Programme	02
	Direct Programme	03
	Direct Programme	04
	Direct Programme	05
	Direct Programme	06
	Direct Programme	07
	Direct Programme	08
	Direct Programme	09
	Direct Programme	00
	Back (Return)	0A
	Volume Decrease -	11
	Volume Increase +	10
	Mute	0D
	Brightness Up	1D
	Brightness Down	1E
	Source	38
	Cursor Up	14
	Cursor Left	15
	OK (Select)	35
	Cursor Right	16
	Cursor Down	13
	Menu	30
	Scheduler	2B
	EXIT	25
	Audio Settings	0F
	Signage	1F
	Aspect Ratio	0B
	Browser	3B
	Picture	26
	dynamic, cinema, game...	33
	PLAY	19
	STOP	18
	PAUSE	31
	SEARCH BACK	1B
	SEARCH FORWARD	1C
	Media Player	39
	Settings URL	3C
	Wireless Display	2F
	Network	22
	SET / UNSET	1A
	INFO	12
	Video Wall Settings	27

DESCRIPTION	SPECIFICATION
Carrier	System clock : 429KHz
Frequency	Carrier : 36 KHz
Operating Voltage	Loaded Voltage 2,6V – 3,4V
Initial Current, whenpressed.	Max. : 30 mA
Stable Current, while pressing.	Max. :15 mA
In idle mode, leakage current.	Max. : 10 uA



Min. Emit Power : 70µw/cm²

DIMENSIONS	
Width	
Length	
Depth	
Weight	

	CONDITION	SPECIFICATION
DROP TEST	Drop the sample with batteries from a height of 80 cm to the ground which is covered with a flat wooden board of 30 mm thickness, the test is performed at 6 faces.	1) No functional failure is allowed 2) No mechanical crack on the product is allowed

	CONDITION	SPECIFICATION
KEYS OPERATING LIFE	Activate the key at the centre with a load of 200 gr at 2 or 3 cycles/sec. Test is done for 50.000 cycles	It must satisfy the specification. Check all products.

	CONDITION	SPECIFICATION
BATTERY LID LIFE	Open and close the battery lid 100 times in or 3 cycles/sec.	Don't close by the weight of the door.

Weee logo should be added.

Recycling logo should be added on Remote Control package

CE CE logo should be added.

There should be rib on 5 key button for blind people.

There should be a label that describes Company Name, system code and batch number.