



DI2 & DO2





DI/DO2

DANTE/AES67 ADAPTER SERIES

Superio Dante/AES67 Adapters

Network all your audio gear easily with Superio DI2 and DO2. They are both plug and play with high performance. DI and DO adapters are automatically discovered and ready to use when connected, and no separate power supplies are required – just use a common PoE (Power over Ethernet)

For further visit: www.superio.com

Part no.	Description
SUP-DI2	Dual input adapter
SUP-DO2	Dual output adapter

Specifications:	
Max output level:	18dBu
Dynamic range:	110dB
Total harmonic distortion THD+N:	0.007% @ 1kHz+4dBu
Signal-to-noise ratio:	>110dB
Freq response:	20Hz - 20kHz (+/-0.2dB)
Connectors:	RJ45 & Dual XLR
Sampling rate:	48kHz
Data bit:	24-bit
Dante Device latency:	<1ms
Power:	1 802.3af PoE

